

Stability of n -Bit Generalized Full Adder Circuits (GFAs). Part II

Katsumi Wasaki
Shinshu University
Nagano, Japan

Summary. We continue to formalize the concept of the Generalized Full Addition and Subtraction circuits (GFAs), define the structures of calculation units for the Redundant Signed Digit (RSD) operations, then prove its stability of the calculations. Generally, one-bit binary full adder assumes positive weights to all of its three binary inputs and two outputs. We define the circuit structure of two-types n -bit GFAs using the recursive construction to use the RSD arithmetic logical units that we generalize full adder to have both positive and negative weights to inputs and outputs. The motivation for this research is to establish a technique based on formalized mathematics and its applications for calculation circuits with high reliability.

MML identifier: GFACIRC2, version: 7.8.09 4.97.1001

The notation and terminology used in this paper have been introduced in the following articles: [15], [2], [12], [17], [1], [7], [8], [3], [6], [13], [16], [14], [11], [10], [9], [4], [5], and [18]. For simplicity the following abbreviations are introduced

$$\begin{aligned}\eta_0 &= \text{Boolean}^0 \mapsto \text{false} \\ \eta_1 &= \text{Boolean}^0 \mapsto \text{true} \\ \Sigma_0 &= 1\text{GateCircStr}(\varepsilon, \eta_0) \\ \Sigma_1 &= 1\text{GateCircStr}(\varepsilon, \eta_1) \\ \mathfrak{C}_0 &= 1\text{GateCircuit}(\varepsilon, \eta_0) \\ \mathfrak{C}_1 &= 1\text{GateCircuit}(\varepsilon, \eta_1)\end{aligned}$$

1. n -BIT GENERALIZED FULL ADDER CIRCUIT (TYPE-0)

Let n be a natural number and let x, y be finite sequences. The functor n -BitGFA0Str(x, y) yielding an unsplit non void strict non empty many sorted signature with arity held in gates and Boolean denotation held in gates is defined by the condition (Def. 1).

- (Def. 1) There exist many sorted sets f, h indexed by \mathbb{N} such that
- (i) n -BitGFA0Str(x, y) = $f(n)$,
 - (ii) $f(0) = \Sigma_0$,
 - (iii) $h(0) = \langle \varepsilon, \eta_0 \rangle$, and
 - (iv) for every element n of \mathbb{N} and for every non empty many sorted signature S and for every set z such that $S = f(n)$ and $z = h(n)$ holds $f(n + 1) = S + \cdot \text{BitGFA0Str}(x(n + 1), y(n + 1), z)$ and $h(n + 1) = \text{GFA0CarryOutput}(x(n + 1), y(n + 1), z)$.

Let n be an element of \mathbb{N} and let x, y be finite sequences. The functor n -BitGFA0Circ(x, y) yields a Boolean strict circuit of n -BitGFA0Str(x, y) with denotation held in gates and is defined by the condition (Def. 2).

- (Def. 2) There exist many sorted sets f, g, h indexed by \mathbb{N} such that
- (i) n -BitGFA0Str(x, y) = $f(n)$,
 - (ii) n -BitGFA0Circ(x, y) = $g(n)$,
 - (iii) $f(0) = \Sigma_0$,
 - (iv) $g(0) = \mathfrak{C}_0$,
 - (v) $h(0) = \langle \varepsilon, \eta_0 \rangle$, and
 - (vi) for every element n of \mathbb{N} and for every non empty many sorted signature S and for every non-empty algebra A over S and for every set z such that $S = f(n)$ and $A = g(n)$ and $z = h(n)$ holds $f(n + 1) = S + \cdot \text{BitGFA0Str}(x(n + 1), y(n + 1), z)$ and $g(n + 1) = A + \cdot \text{BitGFA0Circ}(x(n + 1), y(n + 1), z)$ and $h(n + 1) = \text{GFA0CarryOutput}(x(n + 1), y(n + 1), z)$.

Let n be an element of \mathbb{N} and let x, y be finite sequences. The functor n -BitGFA0CarryOutput(x, y) yields an element of InnerVertices(n -BitGFA0Str(x, y)) and is defined by the condition (Def. 3).

- (Def. 3) There exists a many sorted set h indexed by \mathbb{N} such that n -BitGFA0CarryOutput(x, y) = $h(n)$ and $h(0) = \langle \varepsilon, \eta_0 \rangle$ and for every element n of \mathbb{N} holds $h(n + 1) = \text{GFA0CarryOutput}(x(n + 1), y(n + 1), h(n))$.

The following propositions are true:

- (1) Let x, y be finite sequences and f, g, h be many sorted sets indexed by \mathbb{N} . Suppose that
- (i) $f(0) = \Sigma_0$,
 - (ii) $g(0) = \mathfrak{C}_0$,

- (iii) $h(0) = \langle \varepsilon, \eta_0 \rangle$, and
- (iv) for every element n of \mathbb{N} and for every non empty many sorted signature S and for every non-empty algebra A over S and for every set z such that $S = f(n)$ and $A = g(n)$ and $z = h(n)$ holds $f(n+1) = S + \text{BitGFA0Str}(x(n+1), y(n+1), z)$ and $g(n+1) = A + \text{BitGFA0Circ}(x(n+1), y(n+1), z)$ and $h(n+1) = \text{GFA0CarryOutput}(x(n+1), y(n+1), z)$.
- Let n be an element of \mathbb{N} . Then $n\text{-BitGFA0Str}(x, y) = f(n)$ and $n\text{-BitGFA0Circ}(x, y) = g(n)$ and $n\text{-BitGFA0CarryOutput}(x, y) = h(n)$.
- (2) For all finite sequences a, b holds $0\text{-BitGFA0Str}(a, b) = \Sigma_0$ and $0\text{-BitGFA0Circ}(a, b) = \mathfrak{C}_0$ and $0\text{-BitGFA0CarryOutput}(a, b) = \langle \varepsilon, \eta_0 \rangle$.
- (3) Let a, b be finite sequences and c be a set. Suppose $c = \langle \varepsilon, \eta_0 \rangle$. Then $1\text{-BitGFA0Str}(a, b) = \Sigma_0 + \text{BitGFA0Str}(a(1), b(1), c)$ and $1\text{-BitGFA0Circ}(a, b) = \mathfrak{C}_0 + \text{BitGFA0Circ}(a(1), b(1), c)$ and $1\text{-BitGFA0CarryOutput}(a, b) = \text{GFA0CarryOutput}(a(1), b(1), c)$.
- (4) For all sets a, b, c such that $c = \langle \varepsilon, \eta_0 \rangle$ holds $1\text{-BitGFA0Str}(\langle a \rangle, \langle b \rangle) = \Sigma_0 + \text{BitGFA0Str}(a, b, c)$ and $1\text{-BitGFA0Circ}(\langle a \rangle, \langle b \rangle) = \mathfrak{C}_0 + \text{BitGFA0Circ}(a, b, c)$ and $1\text{-BitGFA0CarryOutput}(\langle a \rangle, \langle b \rangle) = \text{GFA0CarryOutput}(a, b, c)$.
- (5) Let n be an element of \mathbb{N} , p, q be finite sequences with length n , and p_1, p_2, q_1, q_2 be finite sequences. Then $n\text{-BitGFA0Str}(p \hat{\ } p_1, q \hat{\ } q_1) = n\text{-BitGFA0Str}(p \hat{\ } p_2, q \hat{\ } q_2)$ and $n\text{-BitGFA0Circ}(p \hat{\ } p_1, q \hat{\ } q_1) = n\text{-BitGFA0Circ}(p \hat{\ } p_2, q \hat{\ } q_2)$ and $n\text{-BitGFA0CarryOutput}(p \hat{\ } p_1, q \hat{\ } q_1) = n\text{-BitGFA0CarryOutput}(p \hat{\ } p_2, q \hat{\ } q_2)$.
- (6) Let n be an element of \mathbb{N} , x, y be finite sequences with length n , and a, b be sets. Then $(n+1)\text{-BitGFA0Str}(x \hat{\ } \langle a \rangle, y \hat{\ } \langle b \rangle) = (n\text{-BitGFA0Str}(x, y) + \text{BitGFA0Str}(a, b, n\text{-BitGFA0CarryOutput}(x, y)))$ and $(n+1)\text{-BitGFA0Circ}(x \hat{\ } \langle a \rangle, y \hat{\ } \langle b \rangle) = (n\text{-BitGFA0Circ}(x, y) + \text{BitGFA0Circ}(a, b, n\text{-BitGFA0CarryOutput}(x, y)))$ and $(n+1)\text{-BitGFA0CarryOutput}(x \hat{\ } \langle a \rangle, y \hat{\ } \langle b \rangle) = \text{GFA0CarryOutput}(a, b, n\text{-BitGFA0CarryOutput}(x, y))$.
- (7) Let n be an element of \mathbb{N} and x, y be finite sequences. Then $(n+1)\text{-BitGFA0Str}(x, y) = (n\text{-BitGFA0Str}(x, y) + \text{BitGFA0Str}(x(n+1), y(n+1), n\text{-BitGFA0CarryOutput}(x, y)))$ and $(n+1)\text{-BitGFA0Circ}(x, y) = (n\text{-BitGFA0Circ}(x, y) + \text{BitGFA0Circ}(x(n+1), y(n+1), n\text{-BitGFA0CarryOutput}(x, y)))$ and $(n+1)\text{-BitGFA0CarryOutput}(x, y) = \text{GFA0CarryOutput}(x(n+1), y(n+1), n\text{-BitGFA0CarryOutput}(x, y))$.
- (8) For all elements n, m of \mathbb{N} such that $n \leq m$ and for all finite sequences x, y holds $\text{InnerVertices}(n\text{-BitGFA0Str}(x, y)) \subseteq \text{InnerVertices}(m\text{-BitGFA0Str}(x, y))$.
- (9) For every element n of \mathbb{N} and for all finite sequences x, y holds

$\text{InnerVertices}((n+1)\text{-BitGFA0Str}(x, y)) = \text{InnerVertices}(n\text{-BitGFA0Str}(x, y)) \cup \text{InnerVertices}(\text{BitGFA0Str}(x(n+1), y(n+1), n\text{-BitGFA0CarryOutput}(x, y)))$.

Let k, n be elements of \mathbb{N} . Let us assume that $k \geq 1$ and $k \leq n$. Let x, y be finite sequences. The functor $(k, n)\text{-BitGFA0AdderOutput}(x, y)$ yielding an element of $\text{InnerVertices}(n\text{-BitGFA0Str}(x, y))$ is defined as follows:

(Def. 4) There exists an element i of \mathbb{N} such that $k = i + 1$ and $(k, n)\text{-BitGFA0AdderOutput}(x, y) = \text{GFA0AdderOutput}(x(k), y(k), i\text{-BitGFA0CarryOutput}(x, y))$.

Next we state two propositions:

- (10) For all elements n, k of \mathbb{N} such that $k < n$ and for all finite sequences x, y holds $(k+1, n)\text{-BitGFA0AdderOutput}(x, y) = \text{GFA0AdderOutput}(x(k+1), y(k+1), k\text{-BitGFA0CarryOutput}(x, y))$.
- (11) For every element n of \mathbb{N} and for all finite sequences x, y holds $\text{InnerVertices}(n\text{-BitGFA0Str}(x, y))$ is a binary relation.

Let n be an element of \mathbb{N} and let x, y be finite sequences. Observe that $n\text{-BitGFA0CarryOutput}(x, y)$ is pair.

One can prove the following three propositions:

- (12) Let f, g be nonpair yielding finite sequences and n be an element of \mathbb{N} . Then $\text{InputVertices}((n+1)\text{-BitGFA0Str}(f, g)) = \text{InputVertices}(n\text{-BitGFA0Str}(f, g)) \cup (\text{InputVertices}(\text{BitGFA0Str}(f(n+1), g(n+1), n\text{-BitGFA0CarryOutput}(f, g))) \setminus \{n\text{-BitGFA0CarryOutput}(f, g)\})$ and $\text{InnerVertices}(n\text{-BitGFA0Str}(f, g))$ is a binary relation and $\text{InputVertices}(n\text{-BitGFA0Str}(f, g))$ has no pairs.
- (13) For every element n of \mathbb{N} and for all nonpair yielding finite sequences x, y with length n holds $\text{InputVertices}(n\text{-BitGFA0Str}(x, y)) = \text{rng } x \cup \text{rng } y$.
- (14) Let n be an element of \mathbb{N} , x, y be nonpair yielding finite sequences with length n , and s be a state of $n\text{-BitGFA0Circ}(x, y)$. Then $\text{Following}(s, 1 + 2 \cdot n)$ is stable.

2. $n\text{-BIT GENERALIZED FULL ADDER CIRCUIT (TYPE-1)}$

Let n be a natural number and let x, y be finite sequences. The functor $n\text{-BitGFA1Str}(x, y)$ yielding an unsplit non void strict non empty many sorted signature with arity held in gates and Boolean denotation held in gates is defined by the condition (Def. 5).

- (Def. 5) There exist many sorted sets f, h indexed by \mathbb{N} such that
- (i) $n\text{-BitGFA1Str}(x, y) = f(n)$,
 - (ii) $f(0) = \Sigma_1$,
 - (iii) $h(0) = \langle \varepsilon, \eta_1 \rangle$, and

- (iv) for every element n of \mathbb{N} and for every non empty many sorted signature S and for every set z such that $S = f(n)$ and $z = h(n)$ holds $f(n + 1) = S + \cdot \text{BitGFA1Str}(x(n + 1), y(n + 1), z)$ and $h(n + 1) = \text{GFA1CarryOutput}(x(n + 1), y(n + 1), z)$.

Let n be an element of \mathbb{N} and let x, y be finite sequences. The functor $n\text{-BitGFA1Circ}(x, y)$ yielding a Boolean strict circuit of $n\text{-BitGFA1Str}(x, y)$ with denotation held in gates is defined by the condition (Def. 6).

(Def. 6) There exist many sorted sets f, g, h indexed by \mathbb{N} such that

- (i) $n\text{-BitGFA1Str}(x, y) = f(n)$,
- (ii) $n\text{-BitGFA1Circ}(x, y) = g(n)$,
- (iii) $f(0) = \Sigma_1$,
- (iv) $g(0) = \mathfrak{C}_1$,
- (v) $h(0) = \langle \varepsilon, \eta_1 \rangle$, and
- (vi) for every element n of \mathbb{N} and for every non empty many sorted signature S and for every non-empty algebra A over S and for every set z such that $S = f(n)$ and $A = g(n)$ and $z = h(n)$ holds $f(n + 1) = S + \cdot \text{BitGFA1Str}(x(n + 1), y(n + 1), z)$ and $g(n + 1) = A + \cdot \text{BitGFA1Circ}(x(n + 1), y(n + 1), z)$ and $h(n + 1) = \text{GFA1CarryOutput}(x(n + 1), y(n + 1), z)$.

Let n be an element of \mathbb{N} and let x, y be finite sequences. The functor $n\text{-BitGFA1CarryOutput}(x, y)$ yields an element of $\text{InnerVertices}(n\text{-BitGFA1Str}(x, y))$ and is defined by the condition (Def. 7).

(Def. 7) There exists a many sorted set h indexed by \mathbb{N} such that $n\text{-BitGFA1CarryOutput}(x, y) = h(n)$ and $h(0) = \langle \varepsilon, \eta_1 \rangle$ and for every element n of \mathbb{N} holds $h(n + 1) = \text{GFA1CarryOutput}(x(n + 1), y(n + 1), h(n))$.

One can prove the following propositions:

(15) Let x, y be finite sequences and f, g, h be many sorted sets indexed by \mathbb{N} . Suppose that

- (i) $f(0) = \Sigma_1$,
- (ii) $g(0) = \mathfrak{C}_1$,
- (iii) $h(0) = \langle \varepsilon, \eta_1 \rangle$, and
- (iv) for every element n of \mathbb{N} and for every non empty many sorted signature S and for every non-empty algebra A over S and for every set z such that $S = f(n)$ and $A = g(n)$ and $z = h(n)$ holds $f(n + 1) = S + \cdot \text{BitGFA1Str}(x(n + 1), y(n + 1), z)$ and $g(n + 1) = A + \cdot \text{BitGFA1Circ}(x(n + 1), y(n + 1), z)$ and $h(n + 1) = \text{GFA1CarryOutput}(x(n + 1), y(n + 1), z)$.

Let n be an element of \mathbb{N} . Then $n\text{-BitGFA1Str}(x, y) = f(n)$ and $n\text{-BitGFA1Circ}(x, y) = g(n)$ and $n\text{-BitGFA1CarryOutput}(x, y) = h(n)$.

- (16) For all finite sequences a, b holds $0\text{-BitGFA1Str}(a, b) = \Sigma_1$ and $0\text{-BitGFA1Circ}(a, b) = \mathfrak{C}_1$ and $0\text{-BitGFA1CarryOutput}(a, b) = \langle \varepsilon, \eta_1 \rangle$.
- (17) Let a, b be finite sequences and c be a set. Suppose $c = \langle \varepsilon, \eta_1 \rangle$. Then $1\text{-BitGFA1Str}(a, b) = \Sigma_1 + \cdot \text{BitGFA1Str}(a(1), b(1), c)$ and $1\text{-BitGFA1Circ}(a, b) = \mathfrak{C}_1 + \cdot \text{BitGFA1Circ}(a(1), b(1), c)$ and $1\text{-BitGFA1CarryOutput}(a, b) = \text{GFA1CarryOutput}(a(1), b(1), c)$.
- (18) For all sets a, b, c such that $c = \langle \varepsilon, \eta_1 \rangle$ holds $1\text{-BitGFA1Str}(\langle a \rangle, \langle b \rangle) = \Sigma_1 + \cdot \text{BitGFA1Str}(a, b, c)$ and $1\text{-BitGFA1Circ}(\langle a \rangle, \langle b \rangle) = \mathfrak{C}_1 + \cdot \text{BitGFA1Circ}(a, b, c)$ and $1\text{-BitGFA1CarryOutput}(\langle a \rangle, \langle b \rangle) = \text{GFA1CarryOutput}(a, b, c)$.
- (19) Let n be an element of \mathbb{N} , p, q be finite sequences with length n , and p_1, p_2, q_1, q_2 be finite sequences. Then $n\text{-BitGFA1Str}(p \hat{\ } p_1, q \hat{\ } q_1) = n\text{-BitGFA1Str}(p \hat{\ } p_2, q \hat{\ } q_2)$ and $n\text{-BitGFA1Circ}(p \hat{\ } p_1, q \hat{\ } q_1) = n\text{-BitGFA1Circ}(p \hat{\ } p_2, q \hat{\ } q_2)$ and $n\text{-BitGFA1CarryOutput}(p \hat{\ } p_1, q \hat{\ } q_1) = n\text{-BitGFA1CarryOutput}(p \hat{\ } p_2, q \hat{\ } q_2)$.
- (20) Let n be an element of \mathbb{N} , x, y be finite sequences with length n , and a, b be sets. Then $(n+1)\text{-BitGFA1Str}(x \hat{\ } \langle a \rangle, y \hat{\ } \langle b \rangle) = (n\text{-BitGFA1Str}(x, y) + \cdot \text{BitGFA1Str}(a, b, n\text{-BitGFA1CarryOutput}(x, y)))$ and $(n+1)\text{-BitGFA1Circ}(x \hat{\ } \langle a \rangle, y \hat{\ } \langle b \rangle) = (n\text{-BitGFA1Circ}(x, y) + \cdot \text{BitGFA1Circ}(a, b, n\text{-BitGFA1CarryOutput}(x, y)))$ and $(n+1)\text{-BitGFA1CarryOutput}(x \hat{\ } \langle a \rangle, y \hat{\ } \langle b \rangle) = \text{GFA1CarryOutput}(a, b, n\text{-BitGFA1CarryOutput}(x, y))$.
- (21) Let n be an element of \mathbb{N} and x, y be finite sequences. Then $(n+1)\text{-BitGFA1Str}(x, y) = (n\text{-BitGFA1Str}(x, y) + \cdot \text{BitGFA1Str}(x(n+1), y(n+1), n\text{-BitGFA1CarryOutput}(x, y)))$ and $(n+1)\text{-BitGFA1Circ}(x, y) = (n\text{-BitGFA1Circ}(x, y) + \cdot \text{BitGFA1Circ}(x(n+1), y(n+1), n\text{-BitGFA1CarryOutput}(x, y)))$ and $(n+1)\text{-BitGFA1CarryOutput}(x, y) = \text{GFA1CarryOutput}(x(n+1), y(n+1), n\text{-BitGFA1CarryOutput}(x, y))$.
- (22) For all elements n, m of \mathbb{N} such that $n \leq m$ and for all finite sequences x, y holds $\text{InnerVertices}(n\text{-BitGFA1Str}(x, y)) \subseteq \text{InnerVertices}(m\text{-BitGFA1Str}(x, y))$.
- (23) For every element n of \mathbb{N} and for all finite sequences x, y holds $\text{InnerVertices}((n+1)\text{-BitGFA1Str}(x, y)) = \text{InnerVertices}(n\text{-BitGFA1Str}(x, y)) \cup \text{InnerVertices}(\text{BitGFA1Str}(x(n+1), y(n+1), n\text{-BitGFA1CarryOutput}(x, y)))$.

Let k, n be elements of \mathbb{N} . Let us assume that $k \geq 1$ and $k \leq n$. Let x, y be finite sequences. The functor $(k, n)\text{-BitGFA1AdderOutput}(x, y)$ yielding an element of $\text{InnerVertices}(n\text{-BitGFA1Str}(x, y))$ is defined by:

- (Def. 8) There exists an element i of \mathbb{N} such that $k = i + 1$ and $(k, n)\text{-BitGFA1AdderOutput}(x, y) = \text{GFA1AdderOutput}(x(k), y(k))$,

i -BitGFA1CarryOutput(x, y)).

Next we state two propositions:

- (24) For all elements n, k of \mathbb{N} such that $k < n$ and for all finite sequences x, y holds $(k + 1, n)$ -BitGFA1AdderOutput(x, y) = GFA1AdderOutput($x(k + 1), y(k + 1), k$ -BitGFA1CarryOutput(x, y)).
- (25) For every element n of \mathbb{N} and for all finite sequences x, y holds InnerVertices(n -BitGFA1Str(x, y)) is a binary relation.

Let n be an element of \mathbb{N} and let x, y be finite sequences. One can check that n -BitGFA1CarryOutput(x, y) is pair.

We now state three propositions:

- (26) Let f, g be nonpair yielding finite sequences and n be an element of \mathbb{N} . Then InputVertices($(n + 1)$ -BitGFA1Str(f, g)) = InputVertices(n -BitGFA1Str(f, g)) \cup (InputVertices(BitGFA1Str($f(n + 1), g(n + 1), n$ -BitGFA1CarryOutput(f, g))) \setminus { n -BitGFA1CarryOutput(f, g)}) and InnerVertices(n -BitGFA1Str(f, g)) is a binary relation and InputVertices(n -BitGFA1Str(f, g)) has no pairs.
- (27) For every element n of \mathbb{N} and for all nonpair yielding finite sequences x, y with length n holds InputVertices(n -BitGFA1Str(x, y)) = $\text{rng } x \cup \text{rng } y$.
- (28) Let n be an element of \mathbb{N} , x, y be nonpair yielding finite sequences with length n , and s be a state of n -BitGFA1Circ(x, y). Then Following($s, 1 + 2 \cdot n$) is stable.

REFERENCES

- [1] Grzegorz Bancerek. Cardinal numbers. *Formalized Mathematics*, 1(2):377–382, 1990.
- [2] Grzegorz Bancerek. The fundamental properties of natural numbers. *Formalized Mathematics*, 1(1):41–46, 1990.
- [3] Grzegorz Bancerek and Krzysztof Hryniewiecki. Segments of natural numbers and finite sequences. *Formalized Mathematics*, 1(1):107–114, 1990.
- [4] Grzegorz Bancerek and Yatsuka Nakamura. Full adder circuit. Part I. *Formalized Mathematics*, 5(3):367–380, 1996.
- [5] Grzegorz Bancerek, Shin'nosuke Yamaguchi, and Katsumi Wasaki. Full adder circuit. Part II. *Formalized Mathematics*, 10(1):65–71, 2002.
- [6] Czesław Byliński. Finite sequences and tuples of elements of a non-empty sets. *Formalized Mathematics*, 1(3):529–536, 1990.
- [7] Czesław Byliński. Functions and their basic properties. *Formalized Mathematics*, 1(1):55–65, 1990.
- [8] Czesław Byliński. Functions from a set to a set. *Formalized Mathematics*, 1(1):153–164, 1990.
- [9] Yatsuka Nakamura and Grzegorz Bancerek. Combining of circuits. *Formalized Mathematics*, 5(2):283–295, 1996.
- [10] Yatsuka Nakamura, Piotr Rudnicki, Andrzej Trybulec, and Pauline N. Kawamoto. Introduction to circuits, I. *Formalized Mathematics*, 5(2):227–232, 1996.
- [11] Yatsuka Nakamura, Piotr Rudnicki, Andrzej Trybulec, and Pauline N. Kawamoto. Preliminaries to circuits, II. *Formalized Mathematics*, 5(2):215–220, 1996.
- [12] Andrzej Trybulec. Tuples, projections and Cartesian products. *Formalized Mathematics*, 1(1):97–105, 1990.
- [13] Andrzej Trybulec. Many-sorted sets. *Formalized Mathematics*, 4(1):15–22, 1993.
- [14] Andrzej Trybulec. Many sorted algebras. *Formalized Mathematics*, 5(1):37–42, 1996.

- [15] Zinaida Trybulec. Properties of subsets. *Formalized Mathematics*, 1(1):67–71, 1990.
- [16] Edmund Woronowicz. Many–argument relations. *Formalized Mathematics*, 1(4):733–737, 1990.
- [17] Edmund Woronowicz. Relations and their basic properties. *Formalized Mathematics*, 1(1):73–83, 1990.
- [18] Shin’nosuke Yamaguchi, Katsumi Wasaki, and Nobuhiro Shimoi. Generalized full adder circuits (GFAs). Part I. *Formalized Mathematics*, 13(4):549–571, 2005.

Received December 18, 2007
